

Reg. No. :

--	--	--	--	--	--	--	--	--	--	--

Question Paper Code : 27190

B.E./B.Tech. DEGREE EXAMINATION, NOVEMBER/DECEMBER 2015.

Third Semester

Electronics and Communication Engineering

EC 6303 — SIGNALS AND SYSTEMS

(Common to Biomedical Engineering and Medical Electronics Engineering)

(Regulations 2013)

Time : Three hours

Maximum : 100 marks

Answer ALL questions.

PART A — (10 × 2 = 20 marks)

1. Find the value of the integral $\int_{-\infty}^{\infty} e^{-2t} f(t+2) dt$.
2. Give the relation between continuous time unit impulse function $f(t)$, step function $u(t)$ and ramp function $r(t)$.
3. State Dirichlets conditions.
4. Give the relation between Fourier transform and laplace transform.
5. What is $u(t-2) * f(t-1)$? Where $*$ represents convolution.
6. Given the differential equation representation of a system,
$$\frac{d^2}{dt^2} y(t) + 2 \frac{d}{dt} y(t) - 3y(t) = 2x(t)$$
. Find the frequency response $H(jr)$.
7. State the need for sampling.

8. Find the z -transform and its associated ROC for $x[n] = \{1, -1, 2, 3, 4\}$.
9. Distinguish between recursive and non-recursive systems.
10. Convolve the following signals, $x[n] = \{1, 1, 3\}$ and $h[n] = \{1, 4, -1\}$.

PART B — (5 × 16 = 80 marks)

11. (a) Given $x[n] = \{1, 4, 3, -1, 2\}$. Plot the following signals.

(i) $x[-n - 1]$	(ii) $x\left[-\frac{n}{2}\right]$
(iii) $x[-2n + 1]$	(iv) $x\left[-\frac{n}{2} + 2\right]$

Or

- (b) Given the input-output relationship of a continuous time system $y(t) = tx(-t)$. Determine whether the system is causal, stable, linear and time invariant.

12. (a) State and prove any four properties of Fourier transform.

Or

- (b) Find the Laplace transform and its associated ROC for the signal $x(t) = te^{-2|t|}$.

13. (a) Convolve the following signals :

$$x(t) = e^{-2t}u(t - 2)$$

$$h(t) = e^{-3t}u(t)$$

Or

- (b) The input-output of a causal LTI system are related by the differential equation $\frac{d^2}{dt^2} y(t) + 6 \frac{d}{dt} y(t) + 8y(t) = 2x(t)$.

- (i) Find the impulse response $h(t)$
- (ii) Find the response $y(t)$ of this system if $x(t) = u(t)$.

Hint : Use Fourier transform.

14. (a) State and explain sampling theorem both in time and frequency domains with necessary quantitative analysis and illustrations.

Or

- (b) State and prove any two properties of DTFT and any two properties of 2-transform.

15. (a) Convolve the following signals :

$$x[n] = \left(\frac{1}{2}\right)^{n-2} u[n-2]$$

$$h[n] = u[n+2]$$

Or

- (b) Consider an LTI system with impulse response $h[n] = \alpha^n u[n]$ and the input to this system is $x(n) = \beta^n u(n)$ with $|\alpha|$ & $|\beta| < 1$. Determine the response $y[n]$.

(i) When $\alpha = \beta$

(ii) When $\alpha \neq \beta$

Using DTFT.
