



PART – B

(5×13=65 Marks)

11. a) i) Define Dynamically induced EMF and derive it. (5)
- ii) The total core loss of a specimen of silicon steel is found to be 1500 W at 50Hz. Keeping the flux density constant, the loss becomes 3000 W when the frequency is raised to 75 Hz. Calculate separately the hysteresis and eddy current losses at each of those frequencies. (8)

(OR)

- b) i) Explain the AC operation of magnetic circuit. (5)
- ii) A flux density of 1.2 wb/m^2 is required in 1 mm air gap of an electromagnet having an iron path of 1.5 m long. Calculate the mmf required. Given the relative permeability of iron = 1600. (8)
12. a) i) Draw neat circuit diagram of Back-back test method. Also, write the formulas to calculate the power and efficiency. (5)
- ii) A 50 kVA, 11 kV/400 V transformer has a core loss of 500 W and a full load copper loss of 600 W. Calculate the efficiency on unity power factor at full load. Find the load for maximum efficiency and the iron and copper losses corresponding to this load. (8)

(OR)

- b) i) List and explain the conditions for the parallel operation of single phase transformer. (5)
- ii) A 33 kVA, 2200/220 V, 50 Hz, single phase transformer has the following parameters :
- $r_1 = 2.4 \text{ ohm}$, $r_2 = 0.03 \text{ ohm}$, $x_1 = 6 \text{ ohm}$, $x_2 = 0.07 \text{ ohm}$. Calculate
- a) Equivalent resistance, leakage reactance and impedance referred to HV side.
- b) Equivalent resistance, leakage reactance and impedance referred to LV side.
- c) Full load copper loss. (8)

13. a) With neat sketch, explain the multiply excited system of electromechanical energy conversion. (13)

(OR)

- b) Derive the torque equation in round rotor machines. Also, clearly state the assumptions made. (13)



14. a) i) Obtain EMF equation of DC Generator. (5)
ii) A 4 pole wave wound DC motor armature has 880 conductors and delivers 120 A. The brushes have been displaced through 3 angular degrees from the geometrical axis. Calculate
a) The demagnetizing ampere-turns/pole,
b) The cross magnetizing ampere turns/pole
c) The additional field current for neutralizing the demagnetization of the field winding has 1100 turns/pole. (8)

(OR)

- b) i) Briefly explain any one method to improve the commutation. (5)
ii) A compound generator has armature, series and shunt field resistances of 0.8 ohm, 0.2 ohm and 50 ohm respectively and supplies 5 kW at 230 V. Calculate the EMF generated in the armature, when it is connected as (i) long shunt and (ii) short shunt. (8)

15. a) i) Draw and explain the characteristics of DC Shunt Motor. (5)
ii) A DC shunt motor rated 10 kW connected to 250 V supply is loaded to draw 35A armature current running at a speed of 1250 rpm. Given $R_a = 0.5\Omega$.
a) Determine the load torque if the rotational loss is 500 W.
b) Determine the motor efficiency if the shunt field resistance is 250Ω . (8)

(OR)

- b) i) Draw the circuit diagram of Hopkinson's Test and write the merits and demerits of the same. (5)
ii) A 240 V DC series motor takes 40 A when giving its rated output at 1500 rpm. Its armature and field resistance is 0.15Ω and 0.15Ω . Calculate the value of resistance which must be added to obtain rated torque at 1000 rpm. (8)

PART – C

(1×15=15 Marks)

16. a) Draw the equivalent circuit of a single phase 1100/220 V transformer on which the following results were obtained.
1100 V, 0.5 A, 55 W on HV side, LV being open circuited.
10 V, 80 A, 400 W on LV side, HV side being short circuited.
Calculate the voltage regulation and efficiency for the above transformer when supplying 80 A at 0.8 pf lagging. (15)

(OR)

- b) A 400 Volts DC Shunt motor has a no load speed of 1450 rpm. The line current being 9 amperes. At full load condition, the line current is 75 amperes. If the shunt field resistance is 200 ohms, and armature resistance is 0.5 ohm, calculate the full load speed. (15)

101 The first part of the report is devoted to a description of the
 102 experimental apparatus and the methods used for the
 103 measurements. The second part is devoted to a description of the
 104 results obtained and to a discussion of the physical processes
 105 which are thought to be responsible for the observed phenomena.

106 The third part of the report is devoted to a description of the
 107 theoretical model which is used to explain the experimental results.
 108 The fourth part is devoted to a description of the numerical
 109 calculations which have been carried out in order to test the
 110 validity of the theoretical model.

111 The fifth part of the report is devoted to a description of the
 112 conclusions which have been drawn from the results of the
 113 present work. The sixth part is devoted to a description of the
 114 work which is still to be done in this field.

115 The seventh part of the report is devoted to a description of the
 116 acknowledgments which the author wishes to make to the
 117 persons who have helped him in the course of his work.

118 REFERENCES

119 1. J. D. van der Meer, *Physica* **17**, 1 (1950).
 120 2. J. D. van der Meer, *Physica* **18**, 1 (1951).
 121 3. J. D. van der Meer, *Physica* **19**, 1 (1952).
 122 4. J. D. van der Meer, *Physica* **20**, 1 (1953).

123 5. J. D. van der Meer, *Physica* **21**, 1 (1954).
 124 6. J. D. van der Meer, *Physica* **22**, 1 (1955).

125 7. J. D. van der Meer, *Physica* **23**, 1 (1956).