



PART B — (5 × 16 = 80 marks)

11. (a) Design a constant K band pass filter deriving expressions for the circuit components. A constant K highpass filter cuts off at a frequency of 2300 Hz. The load resistance is  $500\Omega$ . Calculate the values of components used in the filter.

Or

- (b) Design a composite high pass filter to operate into a load of  $600\Omega$  and have a cut off frequency of 1.2 KHz. The filter is to have one constant k section, one m-derived section with  $f_{\infty}=1.1\text{KHz}$  and suitably terminated half section. Discuss the merits and demerits of m-derived filter and crystal filter.
12. (a) (i) Derive the transmission line equations and hence obtain expressions for the voltage and current on a transmission line. (10)
- (ii) A transmission line has  $L = 10\text{ mH/m}$ ,  $C = 10^{-7}\text{ F/m}$ ,  $R=20\Omega/\text{m}$  and  $G=10^{-5}\text{ mhos/m}$ . Find the input impedance at a frequency of  $\left(\frac{5000}{2\pi}\right)\text{ Hz}$ , if the line is very long. (6)

Or

- (b) (i) Discuss the types of waveform, distortion introduced by a transmission line. Derive the conditions for the distortionless operation of a transmission line. (10)
- (ii) The characteristic impedance of a Uniform transmission line is  $2309.6\Omega$  at 800 Hz. At this frequency, the propagation constant is  $0.054(0.0366 + j 0.999)$  per km. Determine R and L. (6)
13. (a) Design a single stub matching Network (use Smith chart) for a transmission line functioning at 500 MHz terminated with a load impedance  $= Z_L = 300 + j250\Omega$  and with a characteristic impedance  $Z_0 = 100\text{ ohms}$ . Use short circuited shunt stubs. Determine the VSWR before and after connecting the stub.

Or

- (b) The input impedances of a  $\lambda/8$  long,  $50\Omega$  transmission line are  $Z_1=25+j100\Omega$ ,  $Z_2=10-j50\Omega$ ,  $Z_3=100+j0\Omega$  and  $Z_4=0+j50\Omega$ , when various load impedances are connected at the other end. In each case, determine the load impedance and the reflection coefficient at the input and load ends.



14. (a) Explain the concept of displacement current, in free space  $E = 20 \cos[\omega t - 50x] a_y \text{ v/m}$ . Calculate displacement current density, magnetic field strength and angular frequency.

Or

- (b) Discuss in detail guided waves between parallel planes with neat diagram.
15. (a) (i) Describe the propagation of TE waves in a rectangular waveguide with necessary expressions for the field components. (10)
- (ii) An air filled rectangular waveguide of dimensions  $a = 6 \text{ cm}$  and  $b = 4 \text{ cm}$  operates in the  $\text{TM}_{11}$  mode. Find the cutoff frequency, guide wavelength and phase velocity at a frequency of 3 GHz. (6)

Or

- (b) (i) Describe the principle and operation of rectangular cavity resonators with relevant expressions. (10)
- (ii) Give a brief note on excitation of modes in rectangular waveguides. (6)
-